



# Cembre

151158 E

## COPPER LUGS SHORT BARREL A-M & A-L SERIES



### GENERAL INFORMATION

- UL listed per 486 A up to 35 kV (File nr. E125401).
- The lugs are for use with Cu wire.
- The lugs are manufactured from electrolytic copper tube, annealed to guarantee optimum ductility and electrolytically tin plated to avoid oxidation.
- The tongue is clearly marked with wire size and stud hole dimension.

### INSTALLATION INSTRUCTIONS

- 1) Select proper lug for the Cu wire size used.
- 2) Strip the cable insulation for a length equal to that of the terminal barrel.
- 3) Insert conductor into the barrel.
- 4) Select the proper die as indicated in the table.
- 5) Apply the proper # of crimps, as indicated in the same table.

**Cembre** — [www.cembre.com](http://www.cembre.com)

**Cembre S.p.A.**  
Via Serenissima, 9  
25135 Brescia (Italia)  
Telefono: 030 36921  
Telefax: 030 3365766  
E-mail: [sales@cembre.com](mailto:sales@cembre.com)  
[www.cembre.it](http://www.cembre.it)

**Cembre Ltd.**  
Dunton Park  
Kingsbury Road, Curdworth - Sutton Coldfield  
West Midlands B76 9EB (Great Britain)  
Tel.: 01675 470440 - Fax: 01675 470220  
E-mail: [sales@cembre.co.uk](mailto:sales@cembre.co.uk)  
[www.cembre.co.uk](http://www.cembre.co.uk)

**Cembre S.a.r.l.**  
22 Avenue Ferdinand de Lesseps  
91420 Morangis (France)  
Tel.: 01 60 49 11 90 - Fax: 01 60 49 29 10  
CS 92014 - 91423 Morangis Cédex  
E-mail: [info@cembre.fr](mailto:info@cembre.fr)  
[www.cembre.fr](http://www.cembre.fr)

**Cembre España S.L.**  
Calle Verano, 6 y 8 - Pl. Las Monjas  
28850 Torrejón de Ardoz - Madrid (España)  
Telefono: 91 4852580  
Telefax: 91 4852581  
E-mail: [comercial@cembre.es](mailto:comercial@cembre.es)  
[www.cembre.es](http://www.cembre.es)

**Cembre AS**  
Fossnes Senter  
N-3160 Stokke (Norway)  
Phone: 47 33361765  
Telefax: 47 33361766  
E-mail: [sales@cembre.no](mailto:sales@cembre.no)  
[www.cembre.no](http://www.cembre.no)

**Cembre GmbH**  
Heidemannstraße 166  
80939 München (Deutschland)  
Telefon: 089 3580676  
Telefax: 089 3580677  
E-mail: [sales@cembre.de](mailto:sales@cembre.de)  
[www.cembre.de](http://www.cembre.de)

**Cembre Inc.**  
Raritan Center Business Park  
181 Fieldcrest Avenue  
Edison, New Jersey 08837 (USA)  
Tel.: 732 225-7415 - Fax: 732 225-7414  
E-mail: [Sales.US@cembreinc.com](mailto:Sales.US@cembreinc.com)  
[www.cembreinc.com](http://www.cembreinc.com)



SIZES	CONDUCTOR RANGE			INSTALLATION TOOLING (# of crimps)					
				50 kN		120 - 130 kN		230 kN	520 kN
				6 sh tons		13.5 - 14.6 sh tons		25.8 sh tons	58.4 sh tons
LUGS	[AWG] [MCM]	low str	fine str	HT51 with suffix L, L-KV; RH50, RHM50, B51 with suffix L, A, LA, KV, LA-KV; B500 with suffix A, KV, A-KV	HT120, HT120-KV; HT131 with suffix -C, U-C, LN-C; RHC131 with suffix LN, -KV; RHM132; RHU131-C; B135, B1350, B131, B1300 with suffix C, -CA, LN-C, LN-CA, C-KV, CA-KV, L-C-KV, LN-CA-KV, -UC	ECW-H3D	RHU520		
		[mm²]						DIE SET	NEST + INTENDOR
		A1	12-10 AWG	4 - 6		ME1-50 (1)	-	-	AU230-130D ADAPTER + 130 kN dies
A2	8 AWG	10		ME2-50 (1)	MA2-C+PA10-C (1)	ME2-C (1)			
A3	6 AWG	16		ME3-50 (1)	MA3-C+PA10-C (1)	ME3-C (1)			
A5	4 AWG	25		ME5-50 (1)	MA5-C+PA10-C (1)	ME5-C (1)			
A7	2 AWG	35	25-35	ME7-50 (1)	MA7-C+PA10-C (1)	ME7-C (1)			
A10	2-1/0 AWG	50	35-50	ME10-50 (2)	MA10-C+PA10-C (1)	ME10-C (1)			
A14	1/0-2/0 AWG	70	50-70	ME14-50 (2)	MA14-C+PA24-C (1)	ME14-C (1)			
A19	2/0-3/0 AWG	95	70-95	ME19-50 (2)	MA19-C+PA24-C (1)	ME19-C (1)			
A24	3/0-250 AWG	120	95-120	ME24-50 (2)	MA24-C+PA24-C (1)	ME24-C (1)			
A30	250-300 MCM	150	120-150	ME30-50 (3)	MA30-C+PA48-C (1)	ME30-C (1)			
A37	300-350 MCM	185	150-185	ME37-50 (3)	MA37-C+PA48-C (1)	ME37-C (1)			
A48	350-500 MCM	240	185-240	ME48-50 (3)	MA48-C+PA48-C (1)	ME48-C (2)			
A60	500-600 MCM	300	240-300	-	MA60-C+PA60-C (1)	ME60-C (3)			
A80	600-800 MCM	400	300-400	-	-	ME80-C (3)	ME80-3D (2)	ME80-520 (2)	
A100	800-1000 MCM	500	400-500	-	-	-	ME100-3D (2)	ME100-520 (2)	